Botron High Quality Light weight portable wrist strap checker. Large 2" touch plate for easy testing. Easy to read LED's light s, Low, High and Good. Audible signal will sound when good. Checks all standard wrist straps and coil cords. Has a test range from 500k-10megohms. **Disclaimer.** All statements of technical information are believed to be true and are based upon tests we believe to be reliable. The proper use and application for this product must be the responsibility of the user. The statements herein shall have no force or effect.



PROPERTIES SPECIFICATIONS

- Light weight
- 9 volt battery operated
- LED lights
- >800k-9megohm
- Audible signal when good
- Checks all standard wrist straps and bands
- 3.5"x4.5"x1.5"
- LED lights (3)
- Low R,800K,
- Good 800K-9M
- High R>9M

Insert 9v battery into compartment and plug banana jack from wrist strap into back of unit or cable supplied and with your hand press touch plate. To test just coil cords, unplug coil cord from strap, plug banana end into jack in back of unit with snap end in hand touch coil head to touch plate pressing down. If unit you are testing is good green LED will come on and audible signal will sound.

OTHER PRODUCTS:

B8201 Touch plate wrist strap Tester
B8511 Combo tester, wrist & heel
B82450 Combo testers & stand
B82250 Dual tester & stand
B85501 Wrist Calibration unit
B85502 Combo Calibration unit
B8506 Wall test station
B8525 Deluxe dual test station

Note: After 50,000 test, if the audible signal is no longer heard but green light comes on; replace the battery.

RELATED TEST EQUIPMENT:

B8571 Digital / Analog Megger
B8563 Analog Megger meter
B8530 Constant monitor
B9202 Constant monitor
BSRM-10 10 light surface meter
BSRM-6 6 light surface meter.

BOTRON CO. INC.

325 W. MELINDA LN PHOENIX AZ 85027 PH# 623-582-6700FAX# 623-582-6776 LOW COST BATTERY WRIST STRAP TESTER

sales@botron.com / www.botron.com