



Aqueous Stencil Cleaner

- Cleans solder paste, uncured chip bonders & ink.
- Use on stencils, webbing, frames & misprinted boards.
- Fast cleaning, even inside small stencil apertures.
- Nonflammable, noncorrosive.
- Slow drying for longer cleaning time.
- Non-foaming with low odor.
- Suitable for use in ultrasonic cleaning tanks.

Product Information

Use the MicroCare Aqueous Stencil Cleaner on circuit board assembly lines to clean stencils, frames, boards, and other stencil-printing equipment. It quickly removes lead-free and no-clean solder pastes, and also cleans uncured epoxies and ink. This pump-spray cleaner loosens paste from the smallest apertures, and minimizes the risk of damage to stencils from scrubbing with weaker cleaners.

Aqueous Stencil Cleaner is ideal for room temperature cleaning; no heat is needed. It has a slow drying rate to extend cleaning time. Unlike other water-based products it is nonfoaming and can be used with excellent results in ultrasonic bath cleaning systems.

Safe on all metals, plastics and elastomers. It is noncorrosive and nonflammable.

Also suitable as a general purpose cleaner on stencil printing machinery and fixtures, misprint PCBs, workbenches and tools. It dries residue-free and cleans CRTs, keyboards and other related stencil printer assembly and test equipment.

As an added bonus, individual cartons of spray product include a package of 100-MicroCare Drywipes to make a difficult cleaning job easy.

Technical Details & Cleaning Data

Boiling Point	97°C / 208°F
Chemical Family	Water-Based
Percent Volatile	100%
Odor	Slight, Aromatic
Specific Gravity	0.77

Health, Safety & Environmental Data

Flammable	No
Flashpoint	None
NFPA	Health: 0 Fire: 0 Instability: 0
Organic Content (g/L)	209
RoHS and WEEE Complaint	Yes
REACH	*Yes
GHS / HCS Pictogram	N/A

Packaging

Pump Spray	12 oz / 340 g	MCC-BGA
Minipail	7 lb / 3.15 k	MCC-BGAG
Pail	32 lb / 14.51 k	MCC-BGAP
Drum	400 lb / 181.4 k	MCC-BGAD

TriggerGrip™ compatible	No
Pump Spray Packaging	10 bottles / box
Shelf Life	Unlimited

*Contact MicroCare for specific details

AVAILABILITY: Stocked locally by MicroCare distributors world-wide. Contact MicroCare for a distributor near you. For more information contact MicroCare directly or visit www.MicroCare.com.

Shake before each use. Not recommended for use in stencil printers. Always wear gloves when working with solder paste.

MicroCare Corporation

595 John Downey Drive
 New Britain, CT 06051 USA
 Tel: 860.827.0626
 Fax: 860.827.8105
 Toll-Free: 800.638.0125
 Email: TechSupport@MicroCare.com

MicroCare Europe Bvba

Havendoklaan 19, Cargovil
 Vilvoorde, B-1804 Belgium
 Tel: +32 2 251 95 05
 Fax: +32 2 400 96 39
 Email: EuroSales@MicroCare.com

Discover Perfectly Clean
www.MicroCare.com